



# REPEATER PANEL SEC3000

## FEATURES:

- 7.0 inch color touch-sensitive screen LCD, resolution of 800×480.
- 1 fire alarm relay and 1 fault relay output. Supports upgrade via USB.
- The total number of nodes of Repeater and FACP in the network supports up to 60.
- Supports import and export of configuration data by connecting directly to a PC via the Type-C interface.
- Fire alarm, fault, C&E and operation, each category can store up to 10,000 records.



## DESCRIPTION

The SEC3000 Repeater panel is used as a remote indication and control panel and can communicate with the SEC3004/SEC3008 Fire Alarm Control Panel (FACP) via a CAN or Ethernet network. The SEC3000 is fully functional and has the same display as the FACP, including evacuation/silence/resound and reset functions.

Power Supply	
Operating voltage	18~30V DC
Quiescent current (fully loaded)	< 0.1A

Outputs		
FIRE OUT (+, -)	Output Voltage	18~28V DC
	Max. Output Current	50m A
	End-of-line Resistor	10KΩ
	Cable Diameter	1mm <sup>2</sup> ~ 2.5mm <sup>2</sup>
Fault Out (NC, COM, NO)	Contact Capacity	2A@24VDC
	Cable Diameter	1mm <sup>2</sup> ~ 2.5mm <sup>2</sup>

# REPEATER PANEL SEC3000

Network Communication		
CAN	Output voltage	20 ~ 28VDC
	Max. output current	1A
	End of line resistor	10KΩ
Physical Dimensions		
Approx. Dimensions of the panel (W×H×D)		370×250×125mm
Approx. weight (without battery)		3.5kg

DISTRIBUTED BY:



fb.com/himmaxelectronics  
yt.com/himmaxelectronics  
@himmaxelectronics

sales@himmax.com  
www.himmax.com  
09178229900 / 09998847657  
(02) 8967-6107